




JVC TO CAMLINX BASE CABLE




OUTSIDE VIEW



INSIDE VIEW



OUTSIDE VIEW



INSIDE VIEW

PARTS REQUIRED

ITEM

- 1 6 PIN MINI DIN FREE SOCKET. FARNELL 120-0109
- 2 9 WAY D PLUG & SHELL
- 3 1K RESISTOR 1%
- 4 2.4mm HEATSHRINK SLEEVE. FARNELL 100-8441
- 5 1N914 DIODE. FARNELL 984-3817
- 6 22swg TIN COPPER WIRE
- 7 4 CORE SCREENED CABLE.
CUT LENGTH 5M. FARNELL 119-0168

NOTES.

- SLEEVE ALL SOLDER JOINTS WITH 2.4mm HEATSHRINK SLEEVE
- USE 22SWG TIN COPPER WIRE TO CONNECT PINS 1 & 5 ON D CONNECTOR
- SCREEN IS NOT CONNECTED ON THE D-PLUG

LENGTH 5m

ITEM 1

PIN 1 BROWN _____ TO _____
 PIN 3 ORANGE _____ TO _____
 PIN 4 YELLOW _____ TO _____
 PIN 5 GREEN _____ TO _____
 PIN 6 BLUE _____ TO _____

ITEM 2

PIN 1 & 5
 PIN 1 & 5
 PIN 2 YELLOW
 PIN 3 GREEN
 PIN 4 BLUE



DRWN	CHCD	APP	DATE	ISS
SJH			21-11-12	A

VOLAMP LTD	
DRG NO	TITLE
CAB-CAMLINX-JVC	BASE CABLE